

User Manual

Release 1.21

PAT-Core

Insulation sleeve with built-in separator and optional reference electrode and current collectors



The information in this manual has been carefully checked and believed to be accurate; however, no responsibility is assumed for inaccuracies.

EL-CELL GmbH maintains the right to make changes without further notice to products described in this manual to improve reliability, function, or design. EL-CELL GmbH does not assume any liability arising from the use or application of this product.

EL-Cell GmbH

Tempowerkring 8

21079 Hamburg - Germany

phone: +49 40 79012-737

fax: +49 40 79012-736

e-mail: info@el-cell.com

web: www.el-cell.com

Content

1 Product description	4
2 PAT-Core components	4
3 Unpacking.....	6
4 Pre-use treatment	6
5 Assembly instructions	6
6 Disassembly and cleaning	14
7 Common test cases.....	15
8 Separator features.....	19
9 PAT Components overview	20
10 Technical support.....	23
11 Warranty	23

1 Product description

The PAT-Core is the essential part of the PAT-Cell holding in place and precisely aligning the electrodes under test. The well-defined geometry of the PAT-Core enables high-quality two- and three-electrode tests of Li-ion and other battery materials as well as supercapacitors.



2 PAT-Core components

Every PAT-Core consists of three main parts, all available in different materials.



The **upper plunger**, serving as current collector for the upper electrode



The **insulation sleeve**, fixing the separator and the optional ring reference



The **lower plunger**, serving as current collector for the lower electrode

Figure: Possible configuration of the PAT-Core consisting of stainless steel plungers and insulation sleeve (PP) with separator and reference ring.

2.1 Upper plunger

By default, the upper plunger serves as the negative current collector. The given size fits for any thickness of the upper electrode up to 800 μm . The plungers are available in Stainless Steel (ss), Al and Cu, and as a special version made of PEEK polymer. The PEEK plungers are used in combination with a disc-shaped metal foil as the current collector. Many different metals are available including Au, Pt and Ni.

2.2 Insulation sleeves

Insulation sleeves are available in the materials polypropylen (PP) and PEEK. The inner and outer ring are clipped (PP) or stuck (PEEK) together with a separator or separator-like material (such as a solid state electrolyte) in between. For three-electrode tests, a reference ring can be additionally mounted into the insulation sleeve. An additional reed contact serves as the electrical contact for the reference ring. Different reference ring materials are available including lithium metal, LFP and LTO.




Figure: Components of the insulation sleeve (PP) for 3-electrode testing




Figure: Components of the insulation sleeve (PP) for 2-electrode testing

Insulation sleeves may be ordered ready assembled (PP) or for self-assembly (PP or PEEK). When assembling the insulation sleeve yourself, please use separator circles of 21.6 mm diameter. All parts except the PEEK rings are for single-use.

2.3 Lower plunger

By default, the lower plunger serves as the positive current collector. The choice of materials is the same as for the upper plunger, however, the lower plunger comes in different sizes (height numbers) to account for different thicknesses of the lower electrode and the separator. Available height numbers range between 50 and 800 in steps of 50 μm .

The proper plunger height must be chosen to ensure that the pre-assembled separator is not excessively bent during assembly of the PAT-Core. The proper height number depends on both the thickness of the lower electrode and the thickness of the built-in separator. The following rules apply:

For a separator thickness below 100 µm:

Height number = Thickness of lower electrode (in µm) + 50

For a separator thickness above 100 µm:

Height number = Thickness of lower electrode (in µm) + half of the separator thickness (in µm)

Example: You are using an insulation sleeve with 260 µm glass fiber together with a 90 µm thick LCO cathode. The above equation yields a height number of $90 + 260/2 = 220$. The closest available height number is 200.

3 Unpacking

By default all parts of the PAT-Core can be unpacked in ambient atmosphere before moving inside the glove box. Only the insulation sleeves (PP) must be moved inside vacuum-packed (pouch bag). Please note that some types of insulation sleeves are additionally packed in a can, which is optionally filled with pellets. The can should be opened outside the glove box, it is an outside packing only.

4 Pre-use treatment

All PEEK components such as PEEK rings for sleeve assembly and PEEK plungers must be dried at 80°C in vacuum <0.1 mbar overnight. For convenience, the PEEK plungers may be dried in the assembled state with feed wire and disc spring.

Be cautious when heating polyolefine (PE and PP) components as this may adversely affect their dimensional accuracy. Generally, polyolefine components can be used without prior drying.

5 Assembly instructions

This section describes how the PAT-Core in combination with the compatible test cells has to be assembled in order to conduct proper battery tests.

Note: The assembly has to take place under the protective atmosphere in a glove box.

5.1 Safety precautions

Use proper safety precautions when using hazardous electrode materials and electrolytes. Wear protective glasses and gloves to protect you against electrolyte that may accidentally spill out during disassembly. Upon cell disassembly, dispose all materials properly. Metallic lithium and some insertion compounds may decompose heavily in contact with water and other solvents, and can cause fire.

5.2 PEEK plunger assembly

The following steps describe the assembly and disassembly of the upper and lower PEEK plunger.




Figure: Upper plunger (PEEK)







Figure: Lower plunger (PEEK)

Upper PEEK plunger assembly

1. Insert the upper feed wire into the hole of the upper plunger. Note the correct orientation.





2. Insert the upper disc spring. Make sure the three tabs of the disc spring are properly snapped in.





Lower PEEK plunger assembly

1. Insert the lower feed wire into the hole of the lower plunger. Note the correct orientation.





2. Insert the lower disc spring and turn it clockwise by 45 degrees in order to fix it in place.



Upper PEEK plunger disassembly

1. Lever out the three tabs of the disc spring and remove the disc spring.





2. Remove the upper feed wire.




Lower PEEK plunger disassembly

1. Turn the disc spring counter-clockwise by 45 degrees and lift it out.



2. Remove the lower feed wire.




5.3 PEEK insulation sleeve assembly


The following steps describe the assembly of the PEEK insulation sleeves.

Note: For use with aprotic electrolytes, stick rings and separator must be properly dried upfront, and assembly of the sleeve must be carried out **inside a glove box**.


Recommended drying conditions: Overnight, vacuum, 80°C for stick rings; 160°C for glass fiber separator; room temperature for polyolefin based separator.




1. Insert the reed contact into the outer stick ring



2. Insert the Reference ring on top of the assembly.




3. Insert the separator with diameter 21.6 mm.




4. Put the inner stick ring on top and press it down.



5. Check the proper position of the contact tongue.



5.4 Standard assembly



cell.

11. Attach the cell into a free socket of a PAT docking station.

1. Put the **insulation sleeve (6)** onto the worktop with the smaller side pointing upwards.

2. Insert the **lower electrode (7)** into the sleeve with the active layer facing downwards.

3. Attach the **lower plunger (8)**. The lower plunger is available in different gap sizes in order to account for the thickness of the lower electrode and the separator used.

4. Turn the assembly upside down.

5. Align the contact spring of the sleeve with the horizontal contact pin inside the **cell base (9)**. Then insert the assembly into the cell base.

6. Evenly dispense approx. 100 µl of **electrolyte (5)** on top of the **separator** with a pipette.

Note: The optimum amount of electrolyte will depend on the thickness and porosity of the separator and the electrodes used.

7. Insert the **upper electrode (4)** into the insulation sleeve with the active layer facing downwards.

8. Attach the **upper plunger (3)**.

9. Attach the **screw cap (1)** to the cell base with the wing nut fully released.

10. Tighten the wing nut clockwise in order to seal the

6 Disassembly and cleaning

After disassembly, dispose all single-use components and electrodes properly. If the cell base has got contaminated with electrolyte, clean it with plenty of water and dry with compressed air. Use less electrolyte for subsequent tests. Plungers made of stainless steel have to be cleaned with plenty of water. If necessary, remove persistent dirt with aqueous nitric acid (20%, 2 hours at room temperature). All other cell components are for immediate re-use without cleaning.

Notes:

- Protect yourself against chemical hazards. Electrolyte may spill out during cleaning. Electrode materials and electrolyte may react with ambient atmosphere or solvents used for cleaning. Wear appropriate protection equipment, goggles and gloves.
- Clean all cell parts right after disassembly. Leaving cell parts in contact with ambient atmosphere while still being wetted with electrolyte may result in severe corrosion.

7 Common test cases

These tables show recommended PAT-Core components for the most common testing scenarios and can be used as a guide for building PAT-Cell test cells.

7.1 Testing with aprotic LiPF₆ based electrolytes

Lower electrode (+)	LCO/NCM/LFP/..	LCO/NCM/LFP..	Graphite	Graphite	LCO/NCM/LFP..
Upper electrode (-)	Li metal	Li metal	Li metal	Li metal	Graphite/LTO
Lower plunger	SS or Al	SS or Al	SS or Cu	SS or Cu	SS or Al
Upper plunger	SS or Cu	SS or Cu	SS or Cu	SS or Cu	SS or Cu
Reference	Li metal	none	Li metal	none	Li metal
Separator	FS-5P	FS-5P	FS-5P	FS-5P	FS-5P
T/°C	<70°C	<70°C	<70°C	<70°C	<70°C
Lid seal	PE	PE	PE	PE	PE
Sleeve (single- use)	Insulation sleeve PP (Li-Reference, Separator FS-5P) (10 pcs) ECC1-00-0210-V/X	Insulation sleeve PP (Separator FS- 5P) (10 pcs) ECC1-00-0210- W/X	Insulation sleeve PP (Li-Reference, Separator FS-5P) (10 pcs) ECC1-00-0210-V/X	Insulation sleeve PP (Separator FS-5P) (10 pcs) ECC1-00-0210- W/X	Insulation sleeve PP (Li-Reference, Separator FS-5P) (10 pcs) ECC1-00-0210-V/X

SS = Stainless steel 316L (1.4404)

7.2 Testing with aprotic supercap electrolytes¹

Lower electrode (+)	Activated Carbon (AC)
Upper electrode (-)	AC
Lower plunger	SS or Al
Upper plunger	SS or Al
Reference	Activated carbon on stainless steel
Separator	FS-5P
T/°C	<70°C
Lid seal	PE
Sleeve (single-use)	Insulation sleeve PP (AC(SS)-Reference ring, Separator FS-5P) (10 pcs) ECC1-00-0450-B/X

¹ R₄NBF₄ in acetonitrile or propylene carbonate

AC = Activated carbon

7.3 Testing with aqueous supercap electrolytes

Lower electrode (+)	AC
Upper electrode (-)	AC
Lower plunger	PEEK
Upper plunger	PEEK
Current collector disc	Au
Reference	AC
Separator	GF/A ECC1-01-0011-A/L
T/°C	<70°C
Lid seal	PE
Sleeve (reusable)	Plain Insulation sleeve PEEK, disassembled ECC1-00-0510-T
Reed contact	Au plated SS ECC1-00-0186-D/X
Reference ring	AC ECC1-00-0182-T/X

7.4 Testing with aprotic high-temperature electrolytes

Lower electrode (+)	LCO/NCM/LFP..
Upper electrode (-)	Graphite/LTO
Lower plunger	SS or Al
Upper plunger	SS or Cu
Reference	Li metal
Separator	GF/A ECC1-01-0011-A/L
T/°C	<200°C
Lid seal	PEEK or PTFE
Sleeve (reusable)	Plain Insulation sleeve PEEK, disassembled ECC1-00-0510-T
Reed contact	Ni plated SS ECC1-00-0186-A/X
Reference ring	Li metal plated SS ECC1-00-0182-O/X

8 Separator features

Separator	FS-5P (Freudenberg Viledon FS 2226E+Lydall Solupor 5P09B)	Freudenberg Viledon FS 3005-25	Whatman GF/A
Thickness	220µm	25µm	260µm
Material	PP fiber/PE membrane	PET fiber/Al ₂ O ₃	Borosilicate glass fiber
Porosity	FS: 67%/ 5P: 86%	55%	91%
Wettability	Good	Good	Excellent
Resistance to dendrites	Good	Poor	Modest
Ability for full cell cycle tests	Excellent	Good	Good
Ability for half cell cycle tests (vs. Li)	Excellent	Poor	Modest
Ability for full cell EIS	Excellent	Excellent	Excellent
Ability for half cell EIS	Modest	Poor	Good
Order no (Insulation sleeve (PP) with Li reference)	ECC1-00-0210-V/X	ECC1-00-0210-A/X	ECC1-00-0210-O/X

9 PAT Components overview

The listed items are only an excerpt of the available product range. Please visit el-cell.com for more information.

9.1 Upper plunger

<i>Article Name</i>	<i>Material</i>	<i>Usage</i>	<i>Order number</i>
Upper plunger, Cu	Copper (Cu >99.9%, E-CU 58)	Single-use	ECC1-01-0026-B
Upper plunger, Al	Aluminum (Al >99.5%, EN-AW-1050)	Single-use	ECC1-01-0026-A
Upper plunger, SS	Stainless steel 316L (1.4404)	Reusable	ECC1-01-0026-C
Upper plunger PEEK (Au), assy ¹	PEEK	Reusable*	ECC1-01-0065-A

* chapter 4

¹ including feed wire (Au) and spring disc (Au)

9.2 Lower plunger

<i>Article Name</i>	<i>Material</i>	<i>Usage</i>	<i>Order number</i>
Lower plunger, Al	Aluminum (Al >99.5%, EN-AW-1050)	Single-use	ECC1-01-0027-A_x*
Lower plunger, Cu	Copper (Cu >99.9%, E-CU 58)	Single-use	ECC1-01-0027-B_x*
Lower plunger, SS	Stainless steel 316L (1.4404)	Reusable	ECC1-01-0027-C_x*
Lower plunger PEEK (Au), assy ¹	PEEK	Reusable**	ECC1-01-0055-A_50

* x=Height number, chapter 2.3

** chapter 4

¹ including feed wire (Au) and spring disc (Au)

9.3 Current collector discs

These discs are for use with PEEK plungers. Other materials are available on request.

Article Name	Material	Usage	Order number
Current collector 18 mm, Au (5 pcs)	Gold (Au>99%)	Reusable	ECC1-00-0069-A/V
Current collector 18 mm, Ti (5 pcs)	Titanium (Ti >99%, grade 2)	Reusable	ECC1-00-0069-C/V
Current collector 18 mm, Pt (5 pcs)	Platinum (Pt>99%)	Reusable	ECC1-00-0069-D/V
Current collector 18 mm, Ni (5 pcs)	Nickel (Ni>99%)	Reusable	ECC1-00-0069-F/V

9.4 Reed contacts

Article Name	Material	Usage	Order number
Reed contact (Ni on SS) (10 pcs)	Nickel (Ni>99%) plated Stainless steel 316L (1.4404)	Single-use	ECC1-00-0186-A/X
Reed contact (Au on SS) (10 pcs)	Gold (Au>99%) plated Stainless steel 316L (1.4404)	Reusable	ECC1-00-0186-D/X

9.5 Reference rings

Article Name	Material	Usage	Order number
Reference ring (Mg) (10 pcs)	Magnesium	Single-use	ECC1-00-0182-F/X
Reference ring (Li) (10 pcs)	Lithium	Single-use	ECC1-00-0182-O/X
Reference ring (AC on SS) (10 pcs)	Activated carbon plated Stainless steel 316L (1.4404)	Single-use	ECC1-00-0182-S/X
Reference ring (AC) (10 pcs)	Activated carbon	Single-use	ECC1-00-0182-T/X

9.6 Insulation sleeves

Article Name	Reference material	Separator material	Separator thickness	Order number
Insulation sleeve PP (Li-Reference, Separator FS 3005-25) (10 pcs)	Li metal	PET fiber/Al ₂ O ₃	25 µm	ECC1-00-0210-A/X
Insulation sleeve PP (Separator FS 3005-25) (10 pcs)	-	PET fiber/Al ₂ O ₃	25 µm	ECC1-00-0210-B/X
Plain Insulation sleeve PP (disassembled) (10 pcs)	-	-	-	ECC1-00-0210-D/X
Insulation sleeve PP (Li-Reference, Separator GF/A) (10 pcs) ¹	Li metal	Borosilicate glass fiber	260 µm	ECC1-00-0210-O/X
Insulation sleeve PP (Separator GF/A) (10 pcs)	-	Borosilicate glass fiber	260 µm	ECC1-00-0210-P/X
Insulation sleeve PP (Li-Reference, FS-5P) (10 pcs)	Li metal	PP fiber/PE membrane	220 µm	ECC1-00-0210-V/X
Insulation sleeve PP (Separator FS-5P) (10 pcs)	-	PP fiber/PE membrane	220 µm	ECC1-00-0210-W/X
Insulation sleeve PP (Li-Reference, Separator Customized) (10 pcs)	Li metal	-	-	ECC1-00-0420-A/X
Insulation sleeve PP (AC-Reference ring, Separator FS-5P) (10 pcs)	Activated carbon	PP fiber/PE membrane	220 µm	ECC1-00-0450-D/X
Insulation sleeve PP (AC(SS)-Reference ring, Separator FS-5P) (10 pcs)	Activated carbon on stainless steel	PP fiber/PE membrane	220 µm	ECC1-00-0450-B/X
Insulation sleeve PP (Mg-Reference, Separator GF/A) (10 pcs)	Magnesium	Borosilicate glass fiber	260 µm	ECC1-00-0210-H/X
Plain Insulation sleeve PEEK, disassembled	-	-	-	ECC1-00-0510-T

FS 3005-25 = Freudenberg Viledon FS 3005-25

GF/A = Whatman GF/A

FS-5P = Freudenberg Viledon FS 2226E + Lydall Solupor 5P09B

10 Technical support

Technical support for this product is exclusively provided by EL-Cell GmbH.

EL-Cell GmbH

Tempowerkring 8
21079 Hamburg - Germany

phone: +49 40 79012-737

fax: +49 40 79012-736

e-mail: info@el-cell.com

web: www.el-cell.com

11 Warranty

For a period of one year from the date of shipment, EL-CELL GmbH (hereinafter Seller) warrants the goods to be free from defect in material and workmanship to the original purchaser. During the warranty period, Seller agrees to repair or replace defective and/or nonconforming goods or parts without charge for material or labor, or, at the Seller's option, demand return of the goods and tender repayment of the price. Buyer's exclusive remedy is repair or replacement of defective and nonconforming goods, or, at Seller's option, the repayment of the price.

Seller excludes and disclaims any liability for lost profits, personal injury, interruption of service, or for consequential incidental or special damages arising out of, resulting from, or relating in any manner to these goods.

This Limited Warranty does not cover defects, damage, or nonconformity resulting from abuse, misuse, neglect, lack of reasonable care, modification, or the attachment of improper devices to the goods. This Limited Warranty does not cover expendable items. This warranty is void when repairs are performed by a non-authorized person or service center. At Seller's option, repairs or replacements will be made on site or at the factory. If repairs or replacements are to be made at the factory, Buyer shall return the goods prepaid and bear all the risks of loss until delivered to the factory. If Seller returns the goods, they will be delivered prepaid and Seller will bear all risks of loss until delivery to Buyer. Buyer and Seller agree that this Limited Warranty shall be governed by and construed in accordance with the laws of Germany.

The warranties contained in this agreement are in lieu of all other warranties expressed or implied, including the warranties of merchantability and fitness for a particular purpose.

This Limited Warranty supersedes all prior proposals or representations oral or written and constitutes the entire understanding regarding the warranties made by Seller to Buyer. This Limited Warranty may not be expanded or modified except in writing signed by the parties hereto.